





Please read instructions before commencing installation and retain for future reference.




## Connecting the Terminal Block

Connect main supply (brown - live, blue - neutral, green/yellow - earth) into terminal block making sure all connections are tight.


①




②



③



④



## SPECIFICATIONS:

- **Fitting:** ALUMINIUM + METAL IRON
- **Lamp type:** LED 3W , 3000K.
- **Protection against electric shock:** CLASS I,. Requires earth connection.
- **Ingress Protection:** IP20. Protection against entry of solid objects greater than 12mm in diameter.
- **Quality/Corrosive rating:** QC21: Burning period: 12hrs/24hr cycle. Commercial use, indoor mainly - painted or plated metals. Not for use in corrosive environments.
- **Driver:** Included.

## INSTALLATION INSTRUCTIONS:

**⚠** Electrical products can cause death, injury, or damage to property. Installation of this product must be carried out by a qualified electrician.

- Please obey the concerned regulations and be installed by legal technician.
- To avoid damage to concealed wiring during installation, establish the direction of the supply cable before drilling fixing holes.
- Switch on the wires of the lamp with the same color like the wires of the wall or the cell.  
PE or ⊕ = green/yellow = ground wire
- Separate the wires and the connections away from the heat.
- Use the sleeves to cover the mains supply wiring to the fitting.
- Please avoid the high temperature or humid spaces and keep away from water.

## WARNING:

- Not for outdoor use or in wet conditions.

